

8 / 16 / 24 / 32 Port 17" Cat5 LCD KVM Console (LC1708 / LC1716 / LC1724 / LC1732)









Overview

The 17" CAT5 LC Series KVM switch is a control unit that allows access to multiple computers from an USB KVM console. It allows to access and control up to 8 / 16 / 24 / 32 computers from a single console (keyboard, mouse, and monitor). As many as 256 / 512 / 768 / 1024 computers can be controlled from a single keyboard-monitor-mouse console by cascading to another 31 additional switches. The KVM switch supports USB connections for the console and computers, RJ-45 connectors and CAT 5e/6 cable are used to link to the computers.




| 1 | LCD Monitor | 6 | Touchpad |
|---|----------------------|----|------------------------|
| 2 | Rear Bracket Slot | 7 | Handle |
| 3 | Display Menu Buttons | 8 | Release Switch |
| 4 | Mounting Bracket | 9 | Display Panel |
| 5 | Keyboard | 10 | Port Selection Buttons |

Structure







| 1 | Ground Connection Screw | 4 | Console Port |
|---|-------------------------|---|--------------|
| 2 | Power input(AC) | 5 | PC Port |
| 3 | Power switch | | |


Features

- 17" TFT LCD monitor, high brightness, high resolution
- Metal 19" rack with 1U height
- Ultra slim 99 keys keyboard with small numeric keyboard
- High resolution and high flexibility with touchpad; with two function buttons and scroll wheel, standard USB port

Switch Functions

- Access and control up to 8 / 16 / 24 / 32 computes from a single USB KVM(keyboard, video and mouse) console
- Extending the transmitting distance between the console and the computer 1600*1200@60Hz (50m), 1280*1024@60Hz (100m), 1024*768@60Hz (150m)
- Supports Multiple systems: Windows2000/XP/Vista, Linux, Mac and Sun
- Convenient computer switching via front panel pushbuttons, hotkeys, OSD menu or mouse
- Hot pluggable add or remove computers without having to power down the switch
- Auto scan feature for monitoring user-selected computers
- Broadcast mode operations simultaneously performed on all selected computers
- Keyboard and mouse emulation function

Connection Diagram





Specifications

| Model | | LC1708 | LC1716 | LC1724 | LC1732 | | | | | |
|----------------|-------------------------|--|--------|--------|--------|--|--|--|--|--|
| Computer | Direct | 8 | 16 | 24 | 32 | | | | | |
| connections | Max | 256 | 512 | 768 | 1024 | | | | | |
| Port emulation | Keyboard, mouse | PS/2, USB | | | | | | | | |
| | LCD model | SXGA TFT | | | | | | | | |
| | View area | 17 " | | | | | | | | |
| | Optimum resolution | 1280×1024@60Hz | | | | | | | | |
| LCD monitor | Display color | 16.7 M | | | | | | | | |
| | Brightness | 250cd/m² (T y p) | | | | | | | | |
| | Contrast ratio | 1000 : 1 (T y p) | | | | | | | | |
| | Pixel pitch(mm) | 0.264(H) × 0.264(W) | | | | | | | | |
| Mariaa | X/Y resolution | >1000 points / inch, (40 points/mm) | | | | | | | | |
| Mouse | Touchpad with trackball | Eliminates the need for an external mouse | | | | | | | | |
| Keyboard | | 99 keys (82 keys main keyboard +17 independent small numeric keyboard) | | | | | | | | |
| Port selection | 1 | Pushbuttons, hotkeys, OSD menu, mouse | | | | | | | | |
| Input power | | 100V – 240Vac, 50 ~ 60Hz, <1.5A | | | | | | | | |
| Power consu | mption | 19W | 20W | 21W | 22W | | | | | |
| Operating ter | nperature | 0 – 40 °C | | | | | | | | |
| Store temper | ature | -20 − 60 °C | | | | | | | | |
| Humidity | | 0 – 80% RH, non-condensing | | | | | | | | |
| Net weight | | 13 kg | 13 kg | 13.2kg | 13.2kg | | | | | |
| Product dime | ension (W × D × H) | 448mm×581mm×42.5mm | | | | | | | | |
| Package dim | ension (W × D × H) | 765mm×615mm×185mm | | | | | | | | |
| Optional pow | er input | -36V72V DC | | | | | | | | |